



Product Code

**9700/RA2**

Electrical Actuator  
10Nm 24V 50/60Hz

GO GREEN

STAINLESS STEEL

POLYHEDRA

CLASSIC

## Product use

Actuators can be assembled, using suitable flanged adaptors, to 2-ways ball valves and to manual 3-ways ball valves. They are assembled directly on the motorized 3-ways ball valves. Once this coupling has been performed, the valve can be opened or closed remotely. Alternatively, the actuator can be excluded and the valve can be operated manually.

Castel manufacturers actuator with a variety of operational characteristics: they are manufactured with a synthetic, self-extinguishing housing that covers the motor, the control and cut-out electronics based on the gear reducer torque and the self centring fixing system of the valve rod.

In the event of a power outage to the actuator, the gear reducer can be disengaged using the specific lever, to permit manual use of the valve.

Furthermore, auxiliary contacts for switching are available for remote control of the valve status.

## Product details

|                            |       |
|----------------------------|-------|
| <b>Tensione [V]</b>        | 24    |
| <b>Frequenza [Hz]</b>      | 50/60 |
| <b>Potenza [W]</b>         | 4,8   |
| <b>Grado di protezione</b> | IP 54 |
| <b>Angolo di manovra</b>   | 90°   |

|                                       |                                                                      |
|---------------------------------------|----------------------------------------------------------------------|
| <b>Coppia [Nm]</b>                    | 10                                                                   |
| <b>Tempo di marcia [sec]</b>          | 60                                                                   |
| <b>Temperatura ambiente [°C] min.</b> | -20                                                                  |
| <b>Temperatura ambiente [°C] max.</b> | +50                                                                  |
| <b>Adatto per rubinetto a sfera</b>   | vedere gli accoppiamenti indicati nella tabella SCHEMA ACCOPPIAMENTI |
| <b>Confezione n° pz</b>               | 1                                                                    |

## Notes

- (1) Connessioni elettriche : uscita in commutazione a 2 punti (aperto/chiuso) oppure uscita in continua (0 ÷ 10V)
- (2) Connessioni elettriche : uscita in commutazione a 2 punti (aperto/chiuso)
- (3) Connessioni elettriche : uscita in continua (0 ÷ 10V)